




Doro PhoneEasy[®] 332gsm

easy mobile phone

-  direct memories and SMS button
-  easy keypad and simplified menus
-  clear and loud sound (+30dB)

GSM mobile phone with large keypad, intuitive menus and enlarged text for easy dialling and messaging. Other features include charging cradle, amplified sound and dedicated keys for easier keylock, text messaging and emergency functions.



emergency alert button



doro 

DESIGN BY DORO OF SWEDEN



Doro PhoneEasy[®] 332gsm

Colours: black & white

Calling/Talking

| | |
|--|-----|
| One touch memories | 3 |
| Phonebook with multiple numbers on each name (3, home, mobile, work) | 900 |
| Vcard via SMS | • |
| Top 10 contacts | • |
| Handset volume settings | 7 |
| Speaker phone | • |
| Speaker volume control | 7 |
| Headset outlet | • |
| Headset volume setting | 7 |
| On/off hook button on head set cable support | • |
| Mute function | • |
| Dedicated keylock button | • |
| Auto keylock | • |
| Backlit keypad | • |
| Call timer | • |

Handset LCD display

| | |
|--|----------|
| Menu navigation | • |
| Display type | 1.8 CSTN |
| B/W or colour | Colour |
| Resolution (Pixels / H x W) | 96*128 |
| Display size (mm / H x W) | 27*37 |
| Wallpapers | 8 |
| Backlit display | • |
| Big display font | • |
| Adjustable font size for SMS and phonebook | • |
| Clock & Date | • |
| Languages | 17 |
| Optional display modes optimised for visually impaired users | 3 |

Caller log

| | |
|---------------------------------|----|
| Missed calls | • |
| Received calls | • |
| Outgoing calls | • |
| All calls list | 60 |
| Date & time stamp | • |
| Call number | • |
| Store number (with edit option) | • |

SMS

| | |
|--------------------------|----------------|
| SMS key | • |
| SMS function | Send & receive |
| De-activate SMS function | • |
| Dial embedded numbers | • |
| Store embedded numbers | • |
| Text reply | • |
| Dial back | • |
| Delete single SMS | • |
| Delete all SMS | • |

| | |
|--------------------|---|
| Multiple receivers | • |
| Predictive text | • |

Remote handling

| | |
|--------------------------|---|
| Remote programing option | • |
|--------------------------|---|

Voicemail

| | |
|---|---|
| Voice mail dialing by long press on key 1 | • |
|---|---|

Ringer sound & hearing

| | |
|--|-----|
| Polyphonic ring tones | 10 |
| Ringer volume settings except off | 7 |
| Maximum ringer volume (dB(A) at 1 meter) | >83 |
| Vibration alert | • |
| Key-beep on/off | • |
| Maximum receiving amplification (dB) | 30 |
| Tone control | • |

Network services

| | |
|-----------------------------------|---|
| Call waiting. | • |
| Call forwarding unconditional. | • |
| Call forwarding when busy. | • |
| Call forwarding no answers. | • |
| Call forwarding no service | • |
| Network select . Automatic/manual | • |
| Conference | • |
| SIM toolkit | • |
| Fixed Dialing Number (FDN) | • |

Emergency call settings

| | |
|------------------------------|---|
| Emergency SMS | • |
| Emergency call list dialling | • |

Security

| | |
|---------------------|---|
| Change power on PIN | • |
| SIM pin on/off | • |
| Change SIM pin | • |
| Factory reset | • |

Others

| | |
|--------------------------------|---|
| Wake up alarm | • |
| Calendar | • |
| Torch | • |
| De-activate unwanted functions | • |

Mechanical

| | |
|----------------------------|-----------|
| Size (mm) | 105*50*17 |
| Weight (gram) | 88 |
| Charging pod included | • |
| Easy connect charging plug | • |

Technical

| | |
|--------------------------------|----------------|
| Standby time (hours) | Up to 660 |
| Continuous Talk Time (minutes) | Up to 240 |
| Battery | 1000mAh Li-ion |
| Power adapter | 5V/650mA |
| GSM 850/900/1800/1900 | • |

Doro shall not be held responsible for any errors or omissions contained herein. Specifications are subject to change without notice.

www.doro.com